

## Mini transmitter

### Technical data



## Mini transmitter

<b>Frequency range</b>	470 – 865MHz (specify at time of order)
<b>Switching bandwidth</b>	Up to 40MHz in 25kHz steps
<b>Number of frequency tables</b>	1
<b>Number of factory pre-set frequencies</b>	32
<b>Modulation mode</b>	Wideband FM
<b>Frequency stability</b>	±0.002%
<b>Audio frequency response</b>	50 – 18kHz
<b>Signal-to-noise ratio</b>	>100dB (±45kHz deviation)
<b>Total harmonic distortion</b>	<0.3% typ.
<b>Output power</b>	25mW nominal (50mW option available)
<b>Audio gain control</b>	0-30dB (in 8 steps)
<b>LF cut</b>	2 settings; flat, 80Hz
<b>Input connector</b>	Lemo™ 4 pin locking (3 pin option available)
<b>Control</b>	Infra-red key-fob remote
<b>Battery type</b>	2 x 1.5V alkaline LR3 AAA size
<b>Battery life</b>	5 to 7 hours depending on battery type. Audio recommends using NiMh type batteries
<b>Operating temperature range</b>	-20° C to +55° C
<b>Weight</b>	98 grams (including batteries)
<b>Dimensions</b>	48mm (W) x 82mm (H) x 16.5mm (D)
<b>Accessories</b>	Flexible clear antennae (straight) Neoprene pouch Belt clip

For further information contact Audio Ltd or your local distributor

[www.audioltd.com](http://www.audioltd.com)

As we are always seeking to improve our products, specifications shown are subject to change.